

Rx2 SECOND RX

FT-2000 6K SN.

Δf = 20 KHz

BW = 500 Hz

Remarks

ARRL freq PreAmp. MHz	MDS			in level			IMD			IP3		
	Amp.OFF dBm	Amp.1 dBm	Amp.2 dBm	Amp.OFF dBm	Amp.1 dBm	Amp.2 dBm	Amp.OFF dB	Amp.1 dB	Amp.2 dB	Amp.OFF dBm	Amp.1 dBm	Amp.2 dBm
1,850	-116	-126	-133	-34	-44	-50	82	82	83	6	-4	-9
3,550	-117	-128	-133	-34	-44	-50	83	84	83	7	-3	-9
7,050	-123	-133	-139	-30	-41	-49	93	92	90	16	5	-4
14,200	-123	-133	-141	-31	-42	-49	92	91	92	15	3	-3
21,300	-123	-130	-136	-33	-44	-52	90	86	84	13	0	-9
28,500	-114	-125	-130	-24	-32	-39	90	93	91	21	15	7
50,200	-115	-126	-132	-32	-36	-46	83	90	86	10	9	-3