

ASCII Standard Code Table

v1.0 by IvoMen

March 21, 2008

Donate

A dollar for you worths a million for me. If you find here something useful¹, please *PayPal donate to ivomen@tiscali.it* If you want donate by regular mail², send cute gifts, write a thankful postcard, everything is VERY welcome! *Thanks*³.

ASCII CODE - SYMBOL							
0	NUL Null char	32	(space)	64	@	96	'
1	SOH Start of Heading	33	!	65	A	97	a
2	STX Start of Text	34	"	66	B	98	b
3	ETX End of Text	35	#	67	C	99	c
4	EOT End of Transmission	36	\$	68	D	100	d
5	ENQ Enquiry	37	%	69	E	101	e
6	ACK Acknowledgment	38	&	70	F	102	f
7	BEL Bell	39	'	71	G	103	g
8	BS Back Space	40	(72	H	104	h
9	TAB Horizontal Tab	41)	73	I	105	i
10	LF Line Feed	42	*	74	J	106	j
11	VT Vertical Tab	43	+	75	K	107	k
12	FF Form Feed	44	,	76	L	108	l
13	CR Carriage Return	45	-	77	M	109	m
14	SO Shift Out / X-On	46	.	78	N	110	n
15	SI Shift In / X-Off	47	/	79	O	111	o
16	DLE Data Line Escape	48	0	80	P	112	p
17	DC1 Device Control 1 (oft. XON)	49	1	81	Q	113	q
18	DC2 Device Control 2	50	2	82	R	114	r
19	DC3 Device Control 3 (oft. XOFF)	51	3	83	S	115	s
20	DC4 Device Control 4	52	4	84	T	116	t
21	NAK Negative Acknowledgement	53	5	85	U	117	u
22	SYN Synchronous Idle	54	6	86	V	118	v
23	ETB End of Transmit Block	55	7	87	W	119	w
24	CAN Cancel	56	8	88	X	120	x
25	EM End of Medium	57	9	89	Y	121	y
26	SUB Substitute	58	:	90	Z	122	z
27	ESC Escape	59	;	91	[123	{
18	FS File Separator	60	<	92	\	124	
29	GS Group Separator	61	=	93]	125	}
30	RS Record Separator	62	>	94	^	126	~
31	US Unit Separator	63	?	95	_	127	DEL

To insert ASCII codes: Hold down the "ALT" key, type the ASCII number code on the keyboard number pad, release "ALT" key.

¹Other useful docs/software/websites on <http://ivomen.redirectme.net>

²Ivo Mentuccia - Via delle mele 10 - 00037 Segni (Rm) Italy

³The document is provided "as is" without warranty of any kind :)